



# INTRODUCING THE NEW

## NAD SR 8 SYSTEM REMOTE CONTROL



The latest NAD Classic Series Stereo Integrated Amps and Preamps are being furnished with a newly developed remote handset, the SR8. This new remote is a "Universal NAD" remote that contains the codes for many different NAD products. It also uses the "Device Key" format first introduced on the HTR 2 and an expanded key set that allows for more functionality when compared with the previous Classic Series remotes. The form factor

is similar to our Masters Series remotes providing a more elegant and ergonomic user experience.

This universality also makes the SR 8 the perfect replacement remote for older units. You only need to stock one remote to cover almost all the remote controllable NAD products that have been sold.

### USING THE SR 8 REMOTE CONTROL LIBRARY

The SR 8 can store a different library of default NAD codes for each of its DEVICE SELECTOR "pages."

If the original default library does not control your NAD CD player, DVD player, or other component, follow the procedure below to change the library code. Refer as well to the table below for a list of applicable NAD Library Codes with their corresponding NAD models.

#### Load another library code

##### Example:

Load NAD DVD Player T 517 library codes to SR 8's "CD" device.

- 1 Press and hold [CD] in the DEVICE SELECTOR section of SR 8.
- 2 While holding down the device button (CD), press "2" and "2" using SR 8's numeric buttons. "22" is the corresponding library code for T 517.
- 3 Press [ENTER] while still holding down the device button (CD). The CD device selector will flash once to indicate that the library input is successful. Both the device selector button (CD) and [ENTER] can now be released.

#### Reset the SR 8 to its default settings

The SR 8 can be restored to its factory settings, including default libraries, by the following procedures

- 1 Press and hold [ON] and [DELETE/CLEAR] buttons for about 10 seconds until the AMP device button lights up.
- 2 Within two seconds of the AMP device button lighting up, release both buttons. If the reset mode is successful, the [CD] device button will flash twice.

### TABLE OF LIBRARY CODES APPLICABLE TO SR 8 REMOTE CONTROL

LIBRARY CODE	NAD PRODUCT DESCRIPTION
11	Zone 2
20	Default library for "CD" page; C 515BEE, C 545BEE, C 565BEE
21	T 535, T 585, M55, DVD section of L 54, VISO TWO, VISO FIVE
22	T 513, T 514, T 515, T 517
23	T 587
31	IPD 2
40	Default library for "TUN" page (for C 725BEE built-in tuner); Tuner section of T 175, T 755, T 765, T 775, T 785
41	C 422, C 425
42	C 445

NAD Electronics International reserves the right to change specifications or features without notice. NAD is a registered trademark of NAD Electronics International. All rights reserved. No part of this publication may be reproduced, stored, or transmitted in any form whatsoever without the written permission of NAD Electronics International.

© 01/09 NAD Electronics International.

[www.NADelectronics.com](http://www.NADelectronics.com)